Part Number:
27824BMR

8 Way IR Bypass Signal Booster

distributes TV/FM/DAB signals to 8 different locations

Enhance and extend your signal distribution with the SLx 8 Way IR Bypass Signal Booster. Designed for larger setups, it ensures robust signal distribution with IR bypass compatibility.

Features & Benefits

- Distributes HD TV, Freeview™, DAB, and FM signals across 8 outputs.
- Features 2 inputs (1x TV signal, 1x DAB/FM) for versatile connections.
- Integrated IR bypass compatible with Digi Eye remote control extenders.
- Offers a solid 10dB gain per port, suitable for extensive cable runs or weak signals.
- RED compliant, guaranteeing improved signal handling and reliability.

Product Specifications	
Number of Inputs	**2**
Number of Outputs	**8**
Suitable For	**FM/DAB/TV Ch 21-60 Freeview™**
Frequency Range	**VHF 87-230MHz, UHF 470-790MHz**
Gain	**10dB**
Noise Figure	**Typ. <4dB**
Isolation Between Outlets	**20dB**
Max. Output Level	**84dBµv**
IR Bypass	**5-30MHz + 3dB**
IR Power	**9VDC 15mA SSP**
Impedance	**75Ω**
Power Requirement	**220-240V~50/60Hz, <3W**
Compliance	**RED EN 303 354**

Product Information	
Barcode	**5050171077825**
Units per Pack	**1**
Packaging Size	**38.8 x 5.5 x 10.6cm**
Finished Packaging Weight	**545g**
Outer Box Qty	**20**
Outer Size	**68.5 x 25 x 31.5cm**
Outer Gross Weight	**11.96kg**
Outer Net Weight	**11.37kg**